1 Update on GOSAT TANSO-FTS performance, operations,

2 and data products after more than six years in space

- 3
- 4 A. Kuze¹, H. Suto¹, K. Shiomi¹, S. Kawakami¹, M. Tanaka¹, Y. Ueda¹, A.

5 Deguchi¹, J. Yoshida², Y. Yamamoto³, F. Kataoka⁴, T. E. Taylor⁵, and H. Buijs⁶

- 6 [1]{Japan Aerospace Exploration Agency, Tsukuba-city, Ibaraki, Japan}
- 7 [2]{NEC Cooperation, Fuchu, Tokyo, Japan}
- 8 [3]{NEC Informatec Systems, Ltd., Kawasaki-City, Kanagawa Japan}
- 9 [4] {Remote Sensing Technology Center of Japan, Tsukuba-city, Ibaraki, Japan}
- 10 [5] {Colorado State University, For Collins, CO, U.S.A.}
- 11 [6]{ABB, Inc., Quebec-city, Quebec, Canada}
- 12 Correspondence to: A. Kuze (kuze.akihiko@jaxa.jp)
- 13

14 Abstract

A dataset containing more than six years (February 2009 to present) of radiance-spectra 15 16 for carbon dioxide (CO₂) and methane (CH₄) observations has been acquired by the Greenhouse gases Observing SATellite (GOSAT), nicknamed "Ibuki", Thermal And Near infrared Sensor 17 18 for carbon Observation Fourier-Transform Spectrometer (TANSO-FTS). This manuscript 19 provides updates on the performance of the satellite and TANSO-FTS sensor and describes 20 important changes to the data product, which has recently been made available to users. With 21 these changes the typical accuracy of retrieved column-averaged dry air mole fractions of CO₂ and CH₄ (X_{CO_2} and X_{CH_4}) are 2ppm or 0.5% and 13ppb or 0.7%, respectively. Three major 22 23 anomalies of the satellite system affecting TANSO-FTS are reported: a failure of one of the 24 two solar paddles in May 2014, a switch to the secondary pointing system in January 2015 and 25 most recently, a cryo-cooler shutdown and restart in August 2015. The Level 1A (L1A) (raw interferogram) and the Level 1B (L1B) (radiance spectra) of version V201.201 (V201)
described here have long-term uniform quality and provide consistent retrieval accuracy even
after the satellite system anomalies. In addition, we discuss the unique observation abilities of
GOSAT, made possible by an agile pointing mechanism, which allows for optimization of
global sampling patterns.

6

7 1 Introduction

8 The Greenhouse gases Observing SATellite (GOSAT), launched on 23 January 2009, carries 9 two independent sensors, the Thermal And Near infrared Sensor for carbon Observations 10 Fourier Transform Spectrometer (TANSO-FTS) and the Cloud and Aerosol Imager (TANSO-CAI) (Kuze et al., 2009). The objective of the mission is to provide long term monitoring of 11 column-averaged dry air mole fractions of carbon dioxide (CO₂) and methane (CH₄) (X_{co} and 12 X_{CH.}) over much of the globe. After the Scanning Imaging Absorption Spectrometer for 13 Atmospheric CHartographY (SCIAMACHY) stopped its operation on April 2012 and prior to 14 15 the launch of the Orbiting Carbon Observatory-2 (OCO-2) in July 2014, GOSAT was the only 16 instrument that could provide column amounts of greenhouse gases (GHG) from space (Crisp 17 et al., 2012; Yoshida, et al. 2013). Multiple teams from more than ten countries have been working on independent retrievals of X_{CO_2} and X_{CH_4} with errors of less than 2 ppm (0.5%) 18 19 and 13 ppb (0.7%), respectively, over much of the globe. These datasets have not only reduced uncertainty in global CO₂ flux estimates, but have also been used to monitor regional emissions 20 21 such as CO₂ from mega-cities and CH₄ from oil fields, coal power plants, landfills, and livestock (Kort et al., 2011; Turner et al., 2015). Furthermore, the first high-resolution spectra of plant 22 23 fluorescence from space have presented patterns of gross primary productivity and opened a 24 new viewpoint to the carbon cycle (Frankenberg et al, 2011).

By providing long-term high-resolution spectral data, TANSO-FTS is a pathfinder for the following missions such as the Orbiting Carbon Observatory (OCO-2), which was launched in 2014 (Crisp et al., 2004) and TROPOspheric Monitoring Instrument (TROPOMI), which is scheduled in 2016 (Veefkind et al, 2012). GOSAT and these missions have different observation strategies. TANSO-FTS has wide spectral coverage from SWIR to TIR and an agile pointing system at the expense of spatial context, while OCO-2 and TROPOMI measure GHG with higher spatial resolution using imaging grating spectrometers.

Since launch, the Level 1A (L1A) (raw interferogram) and the Level 1B (L1B) (radiance 1 2 spectra) have been updated ten times: versions of V006, V007, V050, V080, V100, V110, V130, V150, V161, and V201 (Kuze et al., 2012). Kuze et al. (2014) provided the radiance 3 degradation factors (RDF) for long term radiometric correction after launch. Several analyses 4 5 and laboratory experiments have improved the accuracy of the solar lines and molecular line parameters (Toon et al., 2015; Long et al., 2012; Thompson et al., 2012). The accuracy and 6 7 degree of convergence of the retrieval algorithms has been improved by fitting the most 8 persistent spectral residuals with the empirical orthogonal functions (EOF) (O'Dell et al., 2013). 9 These efforts have reduced radiative transfer calculation errors.

10 This paper describes the long-term performance and operation of GOSAT TANSO-FTS. Sect. 2 summarizes improvements of the radiometric and geometric calibrations. Sect. 3 11 12 describes changes to L1B processing and the user product for the new L1B version V201.201 13 (V201) release. Finally, Sect. 4 discusses changes to the TANSO-FTS observation pattern with aim of optimizing the global coverage of the measurement set and providing targeted 14 15 measurements over emission sources such as megacities, oil fields and volcanos. Sect. 5 provides a summary of the changes and discusses the future role of GOSAT in GHG 16 17 observations from space. It also provides an inter-comparison with the newer OCO-2 satellite. The TANSO-CAI radiometric calibration is also described in Sect. 2. 18

19

20 2 Long-term operation and calibrations

The long-term operation of over six years is summarized in Fig. 1 and calibration activity isdescribed in this section.

23 **2.1** Operation before three major anomalies

Except for single-event anomalies caused by cosmic radiation on the star tracker, the mission 24 25 data processor, and the GPS receiver, all the components of the satellite bus and two instruments 26 had been working normally until 24 May 2014. The degree of degradation (DOD) of less than 27 10% of the 4 batteries indicated that power generation degradation was much less than 1% and 28 the satellite bus batteries did not show significant degradation. Enough fuel remained for 14 29 more years of operation as of February 2014, at which point the five year design life-time had 30 passed. Every 2.5 years, an out-of-plane orbit control for the adjustment of the inclination of 31 the orbit phase is performed to keep the local overpass time between 12:46 and 12:51. In July

and August 2011 and December 2013, GOSAT suspended observations several times, and
 during these control periods, observations were collected using the nominal 3-point cross-track
 (CT) scan mode without glint and target observations (Kuze et al, 2012).

4 Kuze et al. (2012) listed the TANSO-FTS items that gradually change with time or occur 5 periodically: (1) the zero path difference (ZPD) shifts in the FTS, (2) the FTS laser signal 6 detection level, and (3) the pointing offset. Up-and-down zero-crossings of laser-fringes (half 7 laser fringe) are utilized for sampling triggers, which result in 76,336 sampling points per 8 interferogram. A fringe counter counts fringes up in the forward scan direction and down in 9 the reverse scan direction. The ideal ZPD positon is the center of the sampling points which is maintained under nominal operation. The occurrence of occasional count errors at the scan 10 11 turnaround causes shift in the ZPD position. Excessive ZPD shifts could lead to spectral 12 resolution changes unless the interferogram is processed with an asymmetric weighting function as described later. The precise same spectral resolution has been maintained for all 13 retrieved spectra either by repositioning ZPD or by applying an asymmetric weighting function 14 15 when the shift is too large. The root cause of the ZPD shift is a combination of degraded laser 16 detection levels, the turnaround time duration of the FTS mechanism, and micro-vibrations of the Earth sensor of the satellite attitude control at 244 Hz. The ZPD shifts had been carefully 17 corrected by shifting the FTS scan position before the bias reaches 50 half laser fringes until 18 19 May 2014. After periodic corrections, the absolute ZPD shift value has been kept lower than 100 laser half-fringes and hence the precise spectral resolution has been maintained for these 20 conditions in all spectral retrievals as shown in Fig. 2. About 70% of the data between July 21 22 2009 and July 2010 and almost 100% of the data between August 2010 and May 2014 are well 23 controlled and not processed with an asymmetric weighting function. The detected laser signal 24 amplitude of dephase and fringe channels indicate that there will be enough margin for future 25 operation, as shown in Fig. 3. The phase delayed dephase signal is used to control the FTS scan direction and the fringe provides the sampling trigger. While the CT motion controlled by the 26 27 micro stepper motor of the TANSO-FTS pointing mechanism assembly is stable, complicated 28 along track (AT) motion has caused fluctuations (Fig. 4). To avoid pointing fluctuations caused 29 by inadequate power to actuate the hardened cable in the primary pointing system, the AT pointing angle range was limited between -16.0 ° (backward) and 19.4 ° (forward) instead of 30 the originally designed $\pm 20^{\circ}$. 31

There is no functional and performance change on orbit in TANSO-CAI since launch except for the gradual radiometric degradation. The dark current levels of the bands 1, 2 and 3 CCD detectors have gradually increased. As of October 2015, 26 out of 512 pixels of the Band 4 InGaAs-detector with complementary metal oxide semiconductor (CMOS) readouts show 5 abnormal large dark level. The integration time for the all 4 bands has not been changed. 6 TANSO-CAI has been operated continuously except for short period after the solar paddle 7 anomaly in May 2014.

8

9 2.2 Solar-paddle-rotation anomaly

10 On 24 May 2014, rotation of one of the two solar paddles stopped, probably because of a single 11 event in the control electronics. The GOSAT satellite computer automatically shut down both TANSO-FTS and CAI. Since the incident, the combination of one rotating and one non-rotating 12 panel has been generating enough power to operate both TANSO-FTS and CAI. From 30 May 13 2014, TANSO-FTS and CAI restarted their observations and are now in full operation. 14 15 However, the FTS ZPD shift has become much faster than before. The most probable cause is 16 a permanent alignment change in the laser detection optics after the sudden cool-down, resulting 17 in a large decrease in signal level on one side of the FTS scan. The FTS scan controller has 18 become more sensitive to micro vibrations. By biasing more than 800 half laser fringes to the 19 side with a higher laser detection level, the ZPD shift becomes much slower but all the data have a ZPD position too far from the center of the interferogram requiring asymmetric 20 21 weighting function processing. Regardless of the biased ZPD position, the radiometric response and spectral positions remain unchanged. After the incident, all the L1B data have 22 23 quality alert flags indicating a ZPD bias larger than 100 half laser fringes. In addition, scans with large ZPD shift from the center of the acquired interferogram have caused false alert flags 24 25 as the center burst was detected as a pointing fluctuation. Scans with large ZPD shifts suffer from resolution degradation when processed with L1B V161. To accommodate this change 26 27 for V161, the Japan Aerospace Exploration Agency (JAXA) is providing the modified 28 instrument line shape function (ILSF) for single-side-biased interferograms.

1 2.3 Pointing instability and switch to secondary mechanism

2 A two-axis pointing system is used by TANSO-FTS to allow both CT and AT motions. In the typical 3-point CT scan mode, the AT mechanism provides slow image motion compensation 3 4 during each 4-second integration for 40.8s and quick turnaround and return of 0.6s with $\pm 6^{\circ}$ mechanical swing motion. Since 3 September 2014, the settling time of the AT pointing of the 5 6 primary system worsened, resulting in an error greater than 0.1° at the beginning of interferogram acquisition. A parameter tuning of the pointing control on 17 November 2014 7 8 did not remedy the problem and the pointing stability continued to decay. Realizing that the 9 primary pointing mechanism might be degraded due to aging of the ball bearings and lubricant. 10 the secondary system was characterized and calibrated over the following one and a half month time period. During this time (since 15 December 2014), the L1B processing was suspended 11 and all the target mode observations were canceled. On 26 January 2015, the pointing was 12 13 switched from the primary pointing system to the secondary system by rotating the optical path 14 selector by 45° as shown in Fig. 4. The pointing settling and stability then became smaller than 0.1°, which is much better than the primary system. The nominal observations with glint and 15 target were then restarted and the AT motor traveling range is once more $+20^{\circ}$ with no angular 16 17 offset. From 30 August 2015, the target mode planning system was resumed allowing users to 18 specify targets of interest with accurate geolocation correction.

19 The TANSO-FTS engineering model (FTS-EM) was operated in a vacuum chamber on the ground to investigate the pointing system behavior after switching to the secondary 20 21 mechanism. Under vacuum, the stiffness of the cable twisting is increased, resulting in reduced 22 AT traveling range. The secondary pointing system indicates cable hardening but the level is 23 much smaller than the primary system. We repeated the hardening both with the FTS-EM 24 mechanism and new cables. Once activating the swing motion in the vacuum and air, the cable 25 shows hardening and softening but no change without motion. Two cycle tests showed that continuous motions changes the stiffness. The data also showed the saturation of the hardening 26 27 after a week-long operation. The hypothesis is that oxidization of the metal cable smooths the 28 swing motion in the air. The ground test result suggests that the secondary pointing system 29 may continue with stable motion in orbit. Once cable hardening is detected, the AT traveling 30 range will need to be reduced as was done for the primary pointing system.

Lessons learned from the operation with the primary pointing system show that the use of wider AT motion with a larger ball bearing rotation can minimize aging effects. In parallel, we have started a periodic diagnostic operation to monitor the cable stiffness and the friction of lubricant and bearing by using full range of AT motion every three days. Except for the initial
 change in December 2014 and January 2015, the secondary pointing mechanism shows no
 significant change in the cable stiffness and friction of the lubricant. Therefore, there is no need
 to reduce the range of the secondary system AT pointing.

5 The AT angular resolver shows AT angle errors larger than 0.1° (sometimes 1°) 6 especially when GOSAT passes over certain areas. These phenomena suggest that angular 7 sensors and readout cables are sensitive to electro-magnetic interference. To minimize 8 mechanical shock to the AT pointing mechanism, since 30 August, 2015 the secondary pointing 9 system is stopped for a short time of less than 1 min over certain areas keeping the FTS 10 mechanism activated.

11

12 **2.4** Cryo-cooler shutdown and temporary TANSO-FTS Band 4 TIR suspension

13 On 2 August, 2015, TANSO-FTS-TIR (Band 4) suspended its data processing due to a sudden 14 shutdown of the cryocooler. The temperature of the band 4 detector increased from 70K to 15 ambient temperature, while the short-wave infrared (SWIR) bands 1, 2 and 3 were operating normally and providing O₂, CO₂, and CH₄ spectra. The most probable root-cause is a single 16 17 event anomaly on the cryocooler control electronics. After the sudden cryocooler mode 18 changed to standby, probably because of the rapid change in thermal balance, the ZPD position 19 of the interferogram shifted rapidly from 800 half laser fringes, crossed the center of the scan, and then to 650 fringes on the opposite side of the center of the scan. The ZPD shift mechanism 20 21 is complicated and it is difficult to simulate the thermal distortion without the large heat source of the cryocooler. For 6 weeks, the bias value of 650 half laser fringes showed a stable condition. 22 23 The new LIB V201 is able to correct the 650 half laser fringes-biased interferogram properly. On September 14, 2015, the cryocooler was restarted successfully. The new ZPD stable 24 25 position after the cooler restart is 1100 half laser fringes, which is on the same side but slightly larger bias than before August 2. After September 15, both SWIR and TIR have been acquired 26 27 simultaneously with nominal grid, target, and glint modes. As Fig. 3 presents, the lower 28 detection level in the future might require a larger ZPD bias to decrease the ZPD shift.

1 2.5 Calibrations

2 2.5.1 Radiometric calibration: response degradation

3 Analytical results from the annual vicarious calibration campaigns (VCC) in Railroad Valley (RRV), Nevada, U.S.A. and monthly on-orbit solar diffuser calibrations show that the absolute 4 radiometric response for both TANSO-FTS-SWIR and TANSO-CAI had rapid initial 5 degradation for the first two years with slower degradation since (Kuze et al, 2011; 2014). The 6 7 relative changes in TANSO-FTS, estimated from the backside diffuser calibration, are now very 8 slow as shown in Fig. 5. The degradation rate is slightly higher for the S-polarization than for 9 the P-polarization in Band 1. The most probable source of the degradation is the FTS beam 10 splitter efficiency. After correction of the Spectralon diffuser bidirectional reflectance 11 distribution function (BRDF) and the distance from the sun, the seasonal variation remains. Possible causes are the temperature-dependent band 1 modulation efficiency, imperfect 12 Spectralon BRDF correction, and earthshine contamination (Toon et al, 2015). The prelaunch 13 data show a temperature dependency in the modulation efficiency. Twice every year, in April 14 or May, and just after the summer time VCC, lunar calibrations have been conducted for both 15 TANSO-FTS and CAI by rotating the satellite and tracking the lunar surface. Except for the 16 6th lunar calibration on 15 July 2011, TANSO-FTS successfully targeted the lunar disk within 17 the instantaneous field of view (IFOV). The phase angle of the moon was within $2-5^{\circ}$ of full 18 19 moon phase for the first four calibrations but was changed to around 7° for 2010 as the lunar 20 BRDF changes rapidly near the full moon. After the solar paddle anomaly, the lunar calibration 21 was suspended to avoid the extreme power consumption of the batteries. The lunar radiometric 22 calibration is consistent with the VCC within their respective error budgets (Shiomi et al., 2013).

23 Since the work published in Kuze et al. (2014), annual VCCs were also performed in 2013, 2014 and 2015, and the data were processed using the same method. Fig. 6 (a) shows the 24 TANSO-FTS RDF by comparing the measured radiance, using prelaunch radiometric 25 26 conversion factor, and forward calculation using surface and radiosonde data together with the 27 RDF model described in Kuze et al. (2014). The results show very slow radiance response degradation. In addition, the 2015 VCC shows there is no significant difference between the 28 29 primary pointing system and the secondary unit. Therefore, there is no need to change the RDF 30 model. These data can be applied to the complete long-term L1B dataset. Fig. 6 (b) indicates 31 no degradation of TANSO-CAI since VCC2011. The error budget of VCC is estimated to be lower than the assigned value of 7%. Inter-comparison with the well-calibrated Visible Infrared 32

Imaging Radiometer Suite (VIIRS) radiometer onboard the Suomi National Polar-orbiting
 Partnership (SUOMI-NPP) also shows long-term agreement with the TANSO-FTS RDF model
 within the allocated error budget (Uprety et. al., 2015).

4 For TIR calibrations of TANSO-FTS Band 4, frequent calibration using the blackbody (BB) and deep space (DS) can remove the response degradation and background radiation. 5 6 During the VCC2011, the systematic error after calibration in each spectral window was 7 analyzed, showing a higher bias of 2K in L1B V130 in radiation from the cold upper atmosphere in the CO₂ band at 650-700cm⁻¹ (Kataoka et al., 2014). The radiometric calibrations are 8 9 modified in V161 and are described in Sect. 3.1. Long-term comparison with sea surface 10 temperatures (SST) monitored by NOAA buoys shows that the difference in monthly means 11 are smaller than 1K over six years (Kataoka et al., 2015).

12

13 **2.5.2 Spectral calibration**

The temperature of the onboard metrology ILSF calibration laser in the FTS mechanism has been well controlled for more than six years. Except for the very gradual changes described in Kuze et al. (2012), the absolute spectral position using Solar Fraunhofer lines and ILSF using the onboard calibration laser indicate very stable spectral characteristics. No correction value has to be considered in the L1B processing and there is no difference between the data from the primary and secondary pointing systems.

20

21 **2.5.3** Geometric calibration and target observation planning

22 The TANSO-FTS primary pointing system has a pointing offset that cannot be detected with 23 an angular resolver (Kuze et al., 2012). The angular telemetry used by geolocation by the L1B 24 algorithm therefore introduces a bias. The pointing offset has been estimated using the onboard camera (CAM). The long-term pointing offset for both grid and target observations is presented 25 in Fig. 7. The offset before January 2015, changed slowly with a monthly time scale. Every 26 two weeks after observation, the best-estimate offset values are updated, and these values are 27 28 provided to GOSAT data users by the National Institute for Environmental Studies (NIES) via 29 the GOSAT user interface gateway (GUIG). The application of these correction values reduces 30 the fluctuation in the geolocation to less than 1km. In planning target mode observations, 31 especially of volcano vents and power plants, applying the offset in advance leads to more

accurate pointing. Target mode planning has been implementing the pointing offset since 5
 August 2013. Target observations are planned two weeks in advance, but the pointing
 correction at the time of the target observation is applied. Generally, with this change plus the
 above-mentioned fluctuation of 1km, the target mode observations have been performed with
 pointing errors less than 2 km.

6 The pointing offset of the secondary pointing mechanism is different. No offset in the 7 angular resolver has as yet been detected. The pointing settling of the secondary system is 8 much more stable than the primary one. However, the optical path selector shown in Fig. 4 was 9 rotated by 45 deg and introduces scene flux as a folding mirror. The axes of the optical path and CT rotation are slightly misaligned, which results in the CT angle-dependent offset. The 10 offset is repeatable and can be well-characterized. The L1B V201 product has corrected 11 geolocations, and the accuracy after correction is better than 0.5 km. For target observations, 12 13 the geometrical offset and misalignment between the GOSAT satellite bus and TANSO-FTS have been implemented from August 30, 2015. At this time, there is no need for additional 14 15 correction using the CAM data.

- 16
- 17 3 Updates to Level 1 products

18 **3.1** Issues in previous versions and L1B V161 modifications

The V150 L1 algorithm is described in detail by Kuze et al. (2012) and Suto et al. (2013a). Two significant modifications to L1B V161 are described here. First, the optical path difference (OPD) sampling interval non-uniformity correction (SINUC) as described in Sect. 2.3.5 of Kuze et al. (2012) was applied in L1B V150. However, a spectral ringing artifact was inadvertently introduced to the spectra in the L1B V150 processing, as 100 zeros were filled in at both ends of the interferogram. The L1B V161 processing switched off SINUC to correct this mistake.

The second significant change to the L1B V161 product is related to the TANSO FTS thermal infrared measurement in spectral band 4. The TIR radiometric validation, performed via comparisons with other satellite and air-borne instruments such as the Scanning Highresolution Interferometer Sounder (S-HIS), indicates that the strong CO₂ absorption band at 660- 700 cm⁻¹ has a high bias (Kataoka et al., 2014). This suggests that the DS obscuration correction applied in L1B V130 and V150 overcorrected the longwave spectra. Further analysis

indicated that the DS view obscuration is unrealistic, given the mechanical alignment and 1 2 pointing offset described in 2.5.3. For the polarization sensitivity correction, we had applied a polarization incident angle of 45°, which was measured prelaunch, for all of the reflecting 3 surfaces. However, some of the mirror surfaces have angles of incidence less than 45° as 4 5 indicated in Fig. 4. For L1B V161 and later, a more accurate polarization reflectance for each 6 mirror was applied by interpolating between discrete reflectance models with incident angles of 35°, 45°, and 55°. This application improves long wave radiometric calibration and the DS 7 8 view correction is no longer applied. Other minor modifications include estimating the direct 9 current (DC) offset by preparing long term look-up-tables with very small gradual timedependence and implementing BB temperature conversions using fine-step look-up-tables 10 instead of interpolating discrete prelaunch calibration data. 11

12

13 **3.2 L1B V201**

14 In this section, the most recent L1B V201 is described. There are three major objectives for 15 this update: modifying Band 1 nonlinearity correction, creating a data product that accurately 16 accommodates the two major anomalies in 2014, and adding information for users' convenience. Nonlinearity introduced by the Band 1 analogue signal chain has been a long-term issue for the 17 18 L1B processing (Suto et al., 2013). First, we address the radiance spectra improvement by 19 correcting the nonlinearity in the interferogram domain via intensity-dependent phase 20 correction (X-axis) in addition to an amplitude correction (Y-axis), as shown in Fig. 8. Then, 21 we describe the reprocessing of the more than six years dataset using the same spectral 22 resolution after correction of the large ZPD shift caused by solar paddle incident and the other 23 corrections. The updated data flow, including modified processing, is shown in Fig. 9. As the ZPD position is largely shift, the L1B V201 algorithm detects the ZPD position before 24 qualification and correction procedures. 25

26

3.2.1 Band 1 nonlinearity and intensity-dependent phase correction

By carefully analyzing more than six years of on-orbit data, we revised the nonlinearity corrections based on the prelaunch test and the tests with the engineering model (EM) in the laboratory after launch. As the Fourier transform spectrometer is based on the linear response

of the instrument, the linearity of the detector, electric parts, and integrated circuit in the 1 2 analogue signal processing chain have to be carefully investigated. All the nonlinear items in 3 the analogue circuits (amplifier, electrical filter, and detector) are corrected in the interferogram 4 domain, as presented in Fig. 8. No corrections were performed in the spectral domain. The 5 identified nonlinear parts of the Band 1 analogue circuit are shown in Fig. 10Fig. 10. The oxygen A (O₂ A) band in Band 1 is used to estimate the effective light-path length with 6 7 modification by scattering. Band 1 also covers solar Fraunhofer lines. The nonlinearity corrections directly improve the Level 2 X_{CO_2} and X_{CH_4} products and chlorophyll fluorescence 8 9 retrieval. Earlier versions of the Band 1 nonlinearity correction was applied in L1B V150 and V161. Assuming that the nonlinearity in the Band 1 analogue circuit mainly occurred in the 10 low-pass filter circuit, it can be expressed as a single set of 3rd order polynomials and corrected 11 (Suto et al., 2011). However, both gain amplifier and the low-pass filter circuit have 12 nonlinearity with different characteristics. It was found that the nonlinearity correction could 13 14 not remove input-level dependent offset and out-of-band artifacts completely.

15 As shown in Fig. 10Fig. 10, the actual analogue circuit consists of four sub modules: 16 the silicon (Si) detector, the high gain amplifier, the low pass filter, and the analogue to digital 17 converter (ADC). The Si detector is highly linear. The ADC non-linearity is difficult to correct as discussed in Kuze et al. (2012). After the release of L1B V150 and V161, we measured the 18 19 intensity-dependent phase delay in the high gain amplifier circuit using the EM model in the 20 laboratory (Suto et al. 2014). The phase delay of the in-orbit circuit should be close to the EM 21 value but needs to be estimated by finding the parameters that minimize out-of-band spectra. The estimated input dependent-phase is shown in Fig. 11Fig. 11. These phases are corrected 22 23 separately by resampling the interferogram in L1B V201, while in V150 and V161 these phases in the high gain amplifier and amplitude nonlinearity in the low pass filter are simultaneously 24 corrected by using a single set of 3rd order polynomials. As the phase is an X-axis error in the 25 26 interferogram, a separate correction is more appropriate. This correction has been implemented in L1B V201. The nonlinearity correction parameters were almost constant but might have 27 small variation. Therefore, multiple iterations are applied as shown in Fig. 9. 28

3.2.2 Large ZPD biased interferogram correction

2 A large ZPD shift causes a change in spectral resolution since the interferogram has fewer samples on one side of the ZPD than on the other side. To provide precisely uniform resolution 3 4 data for the entire mission, a ZPD bias correction is applied to produce the full spectral 5 resolution data from the biased ZPD interferogram as illustrated in Fig. 12Fig. 12. The biased 6 interferogram is multiplied by the weighting function and Fourier transformed using the same 7 length as a normal interferogram. The smooth weighting transitions at the edges are used to 8 limit the artifacts to a very low frequency out of band region. The regions where the weight is 9 2 or 0 varies with the ZPD bias, which is calculated for every interferogram as illustrated in Fig. 9. The largest bias value is 3782 half laser fringes, when the FTS mechanism hits the bumper. 10 11 When the ZPD shift is less than 100 half laser fringes, no weighting function is applied. After June 2014, almost all the data are processed with a weighting function resulting in a slight 12 13 reduction of the signal to noise ratio (SNR) as the number of total sampling points per interferogram is reduced by the bias value. The constant ILSF can be applied to all the L1B 14 15 V201 products. The ILSF model for V201 is provided from NIESNICE GUIG.

16

17 **3.2.3** Corrections for intensity variation and sampling interval non-uniformity

Intensity variation is corrected dividing the interferogram by an interferogram created from the 18 19 low frequency-components such as pointing fluctuation and optical vignetting. During normalization, we used the linear slope of the DC component for L1B V201 instead of boxcar 20 21 DC component used in previous versions. After the intensity variation correction described in Kuze et al. (2012), the interferogram became symmetric and both edges have almost the same 22 23 signal levels. Up to L1B V161, the DC level is subtracted by the linear slope obtained by averaging the 100 edge fringes at both ends of the interferogram. This process sometimes 24 25 creates artifact spectra from linear slope components. For L1B V201, the DC level is subtracted by using a single point at the edge instead of averaging 100 fringe values. The V201 L1B 26 27 algorithm applies SINUC again by modifying the sampling interval non-uniformity model in 28 Fig. 5 in Kuze et al, (2012) to have smooth ends at the maximum OPD. This correction 29 improves the consistency between the forward and backward scanning and removes the ringing 30 artifact structure that existed in V150.

1 3.3 Information added to L1B V201

After more than six years of operation, data processing, and data distribution, there have been many questions and comments from GOSAT users. The answers to frequently asked questions and important and useful ancillary data have been added to the L1B product itself. The modified items are described in the following subsections.

6 3.3.1 Master quality flags

Before launch, quality flags of possible anomalies were prepared, but most of the anticipated 7 8 anomalies never occurred in orbit or remained below the criteria because the temperature of the 9 optics and detectors have been well controlled, and scan speed instability of the FTS mechanism 10 is much less than 2%. These flags have been removed from the L1B V201 products. Only the 11 pointing fluctuation and saturation cause quality degradation. A newly introduced master 12 quality flag identifies poor interferograms resulting from fluctuating pointing. As the data are identified from the measured modulated data, the flag cannot detect poor interferograms when 13 14 fluctuation occurs near the center burst of the interferogram and the surface reflectance is 15 spatially uniform. The ratio of poor data is about 10% and most of the fluctuating data are filtered out. 16

17

18 **3.3.2 Calibration information**

A number of new items have been added to the L1B V201 product data to provide advancedanalysis and for users' convenience.

(i) Best-estimate pointing-location; Although the pointing offset is considered in planning the
target mode observation, the geolocation calculated from the angular resolver and satellite
position data have a pointing offset as described in Sect. 2.3 and summarized in <u>Table 1Table</u>
4, the best-estimated pointing locations are added. The pointing offset is now provided in the
L1B V201.

(ii) Best-estimate radiance conversion for SWIR (bands 1, 2, and 3); The spectral radiance data,
given in units of volt-cm (V cm) have been converted to the calibrated spectral radiance given
in units of W cm⁻¹ str⁻¹ using the prelaunch calibration data. The degradation after launch is
also corrected using RDF provided in Kuze et al. (2014).

(iii) Finite-size IFOV correction for TIR (Band 4); The finite-size of the field of view has a selfapodization effect. Without large degradation of the spectral shape, the self-apodization due to
the size is corrected as described by Knuteson et al. (2004). Together with the original radiance
spectra for atmospheric molecules retrieval, the corrected spectra for Band 4 is added for
meteorological applications.

(iv) Mueller matrix for utilizing two linear polarization data; For SWIR, the input solar scattered 6 7 light is measured in both P and S polarizations separately. The overall optical efficiency of the 8 two linear polarizations, which are combinations of the pointing mirror, the FTS beam splitter, 9 and the aft-optics, differs slightly with pointing angles. Therefore, the instrument polarization of both optical efficiency and phase can be characterized for wide spectral range with a Mueller 10 matrix (Kuze et. al, 2012; O'Brien et al., 2013). 11 The pointing mirror portion of $\mathbf{M}(\theta_{AT},\theta_{CT}) = \mathbf{M}_{\mathbf{r}}(-\theta_{CT})\mathbf{M}_{\mathbf{p}}(\theta_{AT})\mathbf{M}_{\mathbf{m}}(\theta_{AT})\mathbf{M}_{\mathbf{r}}(\theta_{CT})$ in equations (9) and (10) of Kuze et al. 12 (2012) is a function of pointing angles and varies in every measurement. The calculated value 13 for each measurement from the mirror surface reflectivity and its phase is stored in the L1B 14 product later than V201 for users' convenience. As a degradation correction can be applied to 15 16 the radiance calibration portion, the degradation is not included in Mueller matrix.

(v) CAM data with joint photographic experts group (JPEG) format; The onboard CMOS 17 18 camera shown in Fig. 4 is mounted on the optical axis of the TANSO-FTS and can identify the 19 location viewed by the FTS pointing mechanism. CAM has a much higher spatial resolution 20 than TANSO-CAI, and is useful for cloud screening. CAM was originally designed to check 21 the optical alignment after launch. It has been working without degradation beyond its designed 22 life of one year. On the day side, we have been acquiring CAM data every 4s and at least 1 CAM image exists per interferogram. 1 CAM is selected and attached to the L1B showing the 23 24 exact pointing location.

(vi) Scattering angle; Surface reflection and scattering from aerosol and clouds have a strong dependence on geometry. The scattering angle is the angle between the incident sun light direction and scattered light toward GOSAT. It can be calculated from the sun and satellite positons and pointing angles. This value has been added to the L1B V201 for the users' convenience.

(vii) Target mode classification; Calibration and validation sites, large emission sources, and
 volcanos have been targeted in addition to the nominal grid observations. To avoid large biases

in X_{CO₂} and X_{CH₄} due to these targeted enhanced emission sources, target observations are
 categorized and identified so that they may be screened out by the user.

3 (viii) A brief comment as a long name for Hierarchical Data Format (HDF) viewer; TANSO4 FTS is a unique instrument compared to conventional imagers, and some parameters in L1B
5 are specific and not easily understood by users. Brief explanations of the parameters are added
6 as a long name.

7

8 **3.4** Remaining issues with the V201 product after calibration

9 The goal of the calibration and correction is to remove systematic errors. Although, major 10 issues in L1B have been solved in the V201 product, there remain systematic errors equivalent 11 to the random noise level. Both SWIR and TIR have possible sources of systematic residuals 12 between the measured spectra and forward calculations.

13 **3.4.1 SWIR**

The SWIR prelaunch calibrations consisted of 5 nm steps radiance conversion tables for Band 1 and 20 nm steps for bands 2 and 3. After launch, the vicarious calibration uses 1 nm step data but the accuracy is worse than the prelaunch calibration. Finer spectral structure in the radiometric response and their changes, and calibration uncertainty in the spectral structure, causes the residual bias. Studies have shown that shorter wavelengths within a band have larger degradation, especially in bands 1 and 2.

20 As described in Sect. 3.2.1, nonlinearity parameters are selected by minimizing out-ofband artifacts. Real noise and small side lobes are corrected toward zero, and nonlinearity may 21 22 be overcorrected. At present, it is difficult to accurately extract out-of-band artifacts smaller 23 than random noise. As described in Sect. 2.3.2 of Kuze et al. (2012), the 16-bit ADC used in 24 TANSO-FTS have the largest nonlinearity at the center of the dynamic range. The level of the 25 AC-coupled band 1 interferogram is close to zero volt as OPD increases, especially in low input 26 cases. The frequent use of the center bit creates nonlinearity, but there is no correction method 27 at present.

1 3.4.2 TIR

2 Fig. 13 shows the total estimated calibration uncertainty in cases of typical earth radiation and 3 ideal BB target of 280K. Errors in the polarization reflectance, onboard BB emissivity 4 measurement, and the detector nonlinearity correction coefficient, create systematic errors in 5 the spectral radiance. The measured polarization reflectance has much larger error than the 6 scalar reflectance. The temperature differences between the onboard BB and the environment 7 and between the scene and the mirror surface yield errors. Therefore, when TANSO-FTS views 8 cold atmospheres and surfaces, measurement error is larger than the error from viewing the 9 ideal BB target of 280K. The polarization correction is one of the largest error sources. To validate the radiometric calibration and polarization correction, High-performance 10 11 Instrumented Airborne Platform for Environmental Research (HIAPER) Pole-to-Pole Observations (HIPPO) and NOAA buoy data are used as input for forward calibration. In 12 addition, coincident flight data of the airborne S-HIS FTS over Greenland for cold target and 13 over Railroad Valley for hot target are used for spectral radiance comparisons. These results 14 15 suggest the L1B V201 data has spectrally dependent bias equivalent to random noise level. The next L1B version will minimize these systematic errors. Meanwhile, we suggest the following 16 17 bias corrections. The errors are correlated with the background temperature change. The 18 onboard BB temperature with three high resolution thermometers represents the seasonal and 19 orbital-phase variation in instrument environment temperature. The FTS-mechanism and aft-20 optics on the optical bench are temperature-controlled at 23°C. The difference between the 21 environment temperature and the optical bench creates a calibration error. Therefore, the 22 following correction can minimize the bias over the wide target temperature range.

$$R_{corr} = R_{obs} - \{a(\nu) \times (R_{obs} - R(T_{bb})) + b(\nu)\}$$
(1)

where R_{corr}, R_{obs}, and T_{bb}, are corrected and raw observed radiance in W cm⁻¹str⁻¹, and BB temperature, respectively. The scaling factor a(v) and the offset b(v) are both functions of wavenumber γ , and determined from the HIPPO and buoy validation data (Kataoka et al., 2015).

Another issue is the sudden change in TIR signal level, which decreased after the solar paddle incident in May 2014 and increased after the cryo-cooler shutdown in September 2015. Once the signal level changed, it became stable. As there was no water vapor spectral structure in the difference, the most probable cause is the optical alignment or imperfect nonlinearity correction. As the TIR spectra are calibrated six times per orbit, these gaps do not create errors. For the nonlinearity correction, the DC offset level V_{DCoffset} in the equation (1) described in
 Kuze et al. (2014) has to be carefully tuned as it is estimated from the DS view signal. These
 values will be modified in the next version.

4

5 4 Optimizing global coverage

6 The nominal sampling strategy of GOSAT TANSO-FTS is a 3- or 5-point CT scan, along with 7 some special target points such as calibration and validation sites and emission sources. In this 8 section, we discuss ideas and plans for optimizing the usefulness of the GOSAT data collection 9 via changes to the sampling pattern. Some of these ideas could be extended to the planned 10 GOSAT-2 mission, which is tentatively planned for a 2018 launch (Suto et al, 2013b) and the 11 planned OCO-3 mission with a pointing mirror assembly (Eldering et al., 2013).

12 The 2-axis pointing was originally designed for viewing onboard calibration sources and 13 grid point observations. With daily operation planning, the full use of onboard memory in the 14 pointing mechanism controller can be utilized to optimize the global pointing. The agile 15 pointing system permits a large number of custom targets per orbit at the expense of spatial context. It is still difficult to cover the Earth's entire surface with high spectral resolution 16 17 spectrometers such as OCO-2 and TANSO-FTS, which have 16 and 3 day ground track repeat 18 cycles respectively. Therefore, a sampling strategy of these instruments benefits from 19 optimization.

20 Since August 2010, TANSO-FTS has been operating in a 3-point CT scan mode. The exceptions are a 1-point CT scan mode between September 2014 and December 2014 when the 21 22 primary pointing mechanism was unstable, and a short period of 5-point CT scan mode just 23 after TANSO-FTS operation was reset. Thus, measured points were distributed at even 24 distances. The yield rate over cloudy area such as the Amazon, South-east Asia, and Central America, and low surface albedo areas such as snow and ice and bays and channels is very low. 25 26 Areas with thick aerosols such as the Sahara also have larger errors. Generally, flatter and brighter targets provide better spectra for the L2 retrieval algorithms. Now that GOSAT has 27 demonstrated accurate X_{CO_2} and X_{CH_4} remote sensing, demand for emission source 28 29 measurements of mega-cities, power plants, gas fields, and volcanoes has increased. In addition 30 to grid observations, by uploading the pointing angles from the ground every day, TANSO-FTS 31 can target a maximum of about one thousand points per day.

Dithering over fractional cloud areas and targeting coasts and islands, while avoiding bays and channels can increase the yield rate of spectra that provide high quality Level 2 retrievals. Multi-angle observations with cross track, forward, nadir and backward viewing with the two axis-pointing mirror may distinguish aerosol scattering from surface reflection and reduce aerosol-related errors. After the pointing mechanism was switched from the primary to the secondary on 26 January 2015, the secondary shows stable settling and slower cable hardening than the primary system. The optimized target mode allocation can now be considered.

8

9 4.1 Emission source observation

10 Turner et al. (2015) has compared North America CH₄ emissions between the Emission 11 Database for Global Atmospheric Research (EDGAR) v4.2 model, the 2012 US Environmental Protection Agency (EPA) inventory, and the GOSAT Level 2 products. The analytical results 12 show that the EDGAR and EPA bottom-up inventories underestimate a US anthropogenic 13 14 methane source. The emissions are highest in the southern-central US, the Central Valley of 15 California, and Florida wetlands; large isolated point sources such as the US Four Corners also 16 contribute. Compared with CO₂, CH₄ emissions are not well understood. To this end, the 17 sampling of GOSAT paths 35, 36 and 37 over the west coast of North America have been 18 modified by adding targeting of possible large emission sources. For path 35, TANSO-FTS 19 targets coal mining and a power plant at Four Corners. For path 36, TANSO-FTS targets the RRV calibration site three times from the east followed by the Armstrong Flight Research 20 21 Center (AFRC) and the California Institute of Technology (Caltech) which have Total Carbon Column Observing Network (TCCON) validation sites (Wunch et al, 2011). In addition, the 22 23 Chino dairy complex is targeted from Path 36. For the path 37, which occurs the following day, 24 TANSO-FTS targets RRV three times from the west, then three points near Sacramento, 25 California: rice fields, downtown and a landfill. Path 37 also samples Bakersfield, California followed by the AFRC and Caltech sites. For Bakersfield, TANSO-FTS targeted six points 26 27 per path to include upwind and downwind oil fields together with ground and airborne in-situ 28 measurements. This approach, which combines accurate surface, dense airplane and column 29 measurements, was tested in order to estimate the magnitude of the emissions quantitatively 30 using a chemical transport model, without the need for inversion algorithms (Leifer et al., 2015).

1 **4.2** Dithering observation in cloudy areas

2 In order to understand plant respiration and photosynthesis, we attempt to increase the yield rate of high quality L1B spectra that yield good Level 2 over the Amazon, which experiences 3 4 frequent contamination by fractional clouds within the TANSO-FTS 10.5 km IFOV. Since 5 2014, for measurements obtained over the Amazon, we tried dithering observations instead of 6 3 point-CT-scan mode observation. We simply categorized the region into two areas: tropical 7 rain forest (TRF) and Cerrado (CRD). During the dry season, in September 2014, we applied 8 a 3-day dithering observation after the 3-day no-dithering observation. By filtering out clouds 9 with CAM data, 41 (TRF) and 164 (CRD) data remain with dithering while 23 (TRF) and 163 (CRD) remain without dithering, as illustrated in Fig. 14Fig. 14. This experiment showed that 10 dithering increased the clear sky data over TRF during the dry season. Another advantage of 11 dithering is that observation points are increased while a nominal 3-point scan CT mode is used 12 13 to observe the same point three times. For more statistical analysis, we continue the dithering 14 observation for selected target regions.

15

16 **4.3 Extension of glint observation**

17 Uncertainty of the CO₂ uptake estimation can be reduced by extending the latitudinal range of GOSAT glint measurements over oceans. Due to very low reflectance of water surfaces, X_{CO_2} 18 19 can be retrieved only with glint observation, i.e., in nadir viewing the scene is too dark to 20 provide adequate SNR. Until August 2014, the latitudinal range of glint had been ±20° of subsolar point by tracking the exact specular reflection points. Since September, 2014, we have 21 22 extended the glint observation range by tracking not only the exact specular reflection point but 23 also tracking along the principal plane of the GOSAT-sun-specular reflection point on the sea 24 surface. The larger incident angle of the sun has larger reflectance. As illustrated in Fig. 15a, 25 at the time of the autumn equinox, the observed range becomes more than $\pm 40^{\circ}$ in latitude by providing additional data beyond $\pm 20^{\circ}$, where the surface reflectance had been too dark to 26 27 process before. Fig. 15b shows the clear sky data point screened with CAM after glint area 28 extension.

1 4.4 Multi-angle and slant-viewing observation

2 Frankenberg et al. (2012) suggested that it is possible to achieve aerosol-related error reduction 3 using multi-angle measurement with viewing zenith angles of ±30°. Since the AT motion of TANSO is limited $\pm 20^{\circ}$, we have instead measured the RRV vicarious calibration site from the 4 5 eastern orbit of path 36 and the western orbit of path 37 on the next day. Assuming that the 6 surface and atmospheric condition does not change much within a day, the results can be 7 analyzed statistically. From path 37, the sun is located behind GOSAT with the CT angle of 8 +33° producing scattering angle greater than 150°. GOSAT observes brighter backscattered 9 radiation but at the same time, the scattering from aerosol and cloud is larger. On the other hand, the data from path 36 with the CT angle of -20° is less contaminated by aerosol and cloud, 10 which are the largest error sources in the GHG retrieval. At present, we have acquires more 11 12 than 200 sets of measurements for statistical analysis. These datasets can be used to find the 13 best viewing geometry in the future operation to minimize thin cloud and aerosol contamination. 14

15 **5** Summary and Discussion

16 Solutions for two GOSAT system anomalies that occurred on-orbit in 2014 have been found 17 and applied to the new L1B V201 processing. Currently, the satellite bus has enough fuel and four healthy batteries for a decade of observations by TANSO-FTS (both SWIR and TIR) and 18 19 TANSO-CAI. Radiance degradation of TANSO-FTS and CAI has become very slow. The scanning motion of the TANSO-FTS mechanism has been stabilized by biasing the ZPD 20 21 position with low metrology laser detection level. Well-calibrated and user-convenient L1B 22 V201 has been released, and all six years of data are being reprocessed in order to provide the 23 same spectral quality and seamless data. The target mode optimization has improved the number of good data and detected large emission sources, contributing to the effort of detecting 24 25 emissions using satellite data and understanding missing carbon sinks. Especially with careful 26 operation of the mechanical portions, GOSAT will extend its mission life, maximize TANSO-27 FTS performance, and provide a unique dataset.

Even though the number of sampling points per orbit is smaller than for imaging spectrometers, TANSO-FTS has an advantage of wide spectral coverage for both CO₂ and CH₄ in SWIR and TIR. OCO-2 uses grating spectrometers, while GOSAT uses a Fourier transform spectrometer to record spectra near 0.76, 1.6, and 2.0 μm with different observing strategies, integration times, and spatial and spectral resolutions. After the successful launch of OCO-2,

1 measurements from the two independent instruments can be compared to distinguish common 2 forward calculation errors such as line parameters, aerosol scattering, and ocean glint reflection 3 from instrument-specific errors. The multiplexed and large throughput signal from the FTS 4 requires a larger dynamic range and has higher possibility of nonlinearity. Grating 5 spectrometers have more complicated instrument line shape functions and pixel-to-pixel non-6 uniformity. These characteristics have to be properly modeled in the retrieval process. The 7 initial steps of this inter-comparison are (1) radiometric comparison from a common vicarious 8 calibration site at RRV in Nevada, where surface reflectance and BRDF have been characterized over six years and $X_{\rm CO_2}$ data are also available from air-borne and ground-based 9 10 instruments, (2) spectral comparisons from the lunar calibration data, and (3) comparisons of X_{CO_2} from spatially and temporally coincident observations such as Lamont, AFRC, Caltech 11 12 TCCON sites. Once the two instruments are characterized, they can view common targets from 13 different geometries (Kuze et al, 2015). This capability provides additional constraints on aerosol scattering, which is the largest uncertainty for CO₂ retrieval from space. 14

Globally-consistent observation of greenhouse gases from space is still challenging especially at high latitude and over very bright desert surfaces with thick aerosol. However, a detailed understanding of the carbon cycle requires global satellite data. Further applications, validations and new algorithms, such as those presented above, should be investigated for full use of GOSAT data;

(i) TIR and SWIR synergetic observations; thermal emission from the atmosphere contains
vertical density distribution information due to the temperature gradient. With a column density
constraint from SWIR, the difference between the upper and lower troposphere can be retrieved,
which will contribute to a better understanding of the dynamics.

(ii) Simultaneous observation of two liner polarizations; TANSO-FTS is the only space borne
instrument that measures two linear polarizations with high spectral resolution. This capability
has the potential to provide improved retrieval of cloud and aerosol (Sanghavi et al., 2015).

(iii) Validation with the medium gain; global GOSAT observations cover a wide range of
surface albedos (Kawakami et al, 2015). The nonlinearity correction is the most complicated in
the L1B processing routine. Except for TCCON at AFRC, all the TCCON sites are located at
medium or low albedo areas. Light path modifications are complicated with aerosol at high
albedo areas and retrieval becomes more difficult.

- 1
- 2

3 Acknowledgements

The authors would like to thank J. Katoh, N. Goto, Y. Aketa, S. Funaki, and Y. Tsukahara of the GOSAT operation team, A. Sasaki and S. Obara of the JAXA tribology laboratory, T. Arai of Fujitsu Corporation, K. Ikehara of NEC Corporation, F. Komagata, K. Nakagawa, and Hashizume of Mitsubishi Electric Corporation, Y. Yoshida and T. Yokota of the NIES GOSAT team, the JPL OCO-2 calibration team led by C. Bruegge and F. Schwandner, the RemoteC team led by A. Butz at Karlsruhe Institute of Technology, and the SSEC team led by R. Knuteson at the University of Wisconsin.

11

12 **References**

13 Crisp, D., Atlas, R. M., Bréon, F.-M., Brown, L. R., Burrows, J. P., Ciais, P., Connor, B. 1. 14 J., Doney, S. C., Fung, I. Y., Jacob, D. J., Miller, C. E., O'Brien, D., Pawson, S., Randerson, 15 J. T., Rayner, P., Salawitch, R. J., Sander, S. P., Sen, B., Stephens, G. L., Tans, P. P., Toon, G. C., Wennberg, P. O., Wofsy, S. C., Yung, Y. L., Kuang, Z., Chudasama, B., Sprague, 16 17 G., Weiss, B., Pollock, R., Kenyon, D., and Schroll, S.: The Orbiting Carbon Observatory 18 (OCO) mission, Adv. Space Res., 34, 700-709, doi:10.1016/j.asr.2003.08.062, 2004. 19 2. Crisp, D., Fischer, B. M., O'Dell, C., Frankenberg, C., Basilio, R., Bösch, H., Brown, L. 20 R., Castano, R., Connor, B., Deutscher, N. M., Eldering, A., Griffith, D., Gunson, M., Kuze, 21 A., Mandrake, L., McDuffie, J., Messerschmidt, J., Miller, C. E., Morino, I., Natraj, V., 22 Notholt, J., O'Brien, D., Oyafuso, F., Polonsky, I., Robinson, J., Salawitch, R., Sherlock, 23 V., Smyth, M., Suto, H., Taylor, T., Thompson, D. R., Wennberg, P. O., Wunch, D., and 24 Yung, Y. L.: The ACOS X_{CO2} retrieval algorithm, Part II: Global X_{CO2} data characterization, 25 Atmos. Meas. Tech., 5, 1-21, 2012. 26 3. Eldering A., Kaki, S., Crisp, D., and Gunson. M.R.: The OCO-3 mission, San Francisco, 27 AGU fall meeting, 2013. 28 4. Frankenberg, C., Fisher, J. B., Worden, J., Badgley, G., Saatchi, S. S., Lee, J.-E., Toon, G.

C., Butz, A., Jung, M., Kuze, A., and Yokota, T.: New global observations of the terrestrial
carbon cycle from GOSAT: Patterns of plant fluorescence with gross primary productivity,
Geophys. Res. Lett., 38, L17706, doi:10.1029/2011GL048738, 2011.

- Frankenberg, C., Hasekamp, O., O'Dell, C., Sanghavi, S., Butz, A., and Worden J.: Aerosol
 information content analysis of multi-angle high spectral resolution measurements and its
 benefit for high accuracy greenhouse gas retrievals, Atmos. Meas. Tech., 5, 1809-1821,
 2012.
- 5 <u>6.</u> GOSAT <u>userdata</u> interface gateway, available at
- 6 <u>https://data.gosat.nies.go.jp/GosatUserInterfaceGateway/guig/GuigPage/openTechInfo.do</u>
 7 <u>https://data.gosat.nies.go.jp/GosatUserInterfaceGateway/guig/techInfo/TFTSILFS.html.</u>
- 6.7. Kataoka, F., Knuteson, R. O., Kuze, A., Suto, H., Shiomi, K., Harada, M., Garms, E. M.,
 Roman, J., Tobin, D. C., Taylor, J., Revercomb, H. E., Sekio, N., Higuchi, R., and Mitomi,
 Y.: TIR Spectral radiance calibration of the GOSAT satellite borne TANSO-FTS with the
 aircraft-based S-HIS and the ground based S-AERI at the Railroad Valley Desert playa,
 IEEE Trans. Geosci. Remote Sensing, 52, 89- 105, doi:10.1109/TGRS.2012.2236561,
 2014.
- 7.8. Kataoka, F., Knuteson, R. O., Kuze, A., Shiomi, K., Suto, H., Saitoh, N.: GOSAT TIR
 radiometric validation toward simultaneous GHG column and profile observation, AGU
 fall meeting, San Francisco, 2015.
- Kawakami, S., Kuze, A., Hillyard, P. W., Podolske, J., Tanaka, T., Iraci, L., Albertson, R.,
 Butz, A., Kataoka, F., Murakami, K., Shiomi, K., Katoh, E., and Suto, H.,: A compact
 automated FTS at the desert playa for satellite validation of the total column CO₂ and CH₄,
 Fourier Transform Spectroscopy and Hyperspectral Imaging and Sounding of the
 Environment, OSA Technical Digest (Optical Society of America, 2015), paper FW3A.2,
 2015.
- 9.10. Knuteson, R. O., Revercomb, H. E., Best, F. A., Ciganovich, N. C., Dedecker, R. G.
 Dirkx, T. P., Ellington, S. C., Feltz, W. F., Garcia, R. K., Howell, H. B., Smith, W. L.,
 Short, J. F., and Tobin, D. C.: Atmospheric Emitted Radiance Interferometer. Part II:
 Instrument Performance, J. Atmos. Oce. Tec., 21, 1777-1789, 2004.
- 10.11. Kort, E. A., Frankenberg, C., Miller, C. E., and Oda T.: Space-based observations of
 megacity carbon dioxide, Geophys. Res. Lett., 39, L17806, doi:10.1029/2012GL052738,
 2012.
- 30 <u>11-12.</u> Kuze, A., Suto, H., Nakajima, M., and Hamazaki, T.: Thermal and near infrared sensor
 31 for carbon observation Fourier-transform spectrometer on the Greenhouse Gases
- 32 Observing Satellite for greenhouse gases monitoring, Appl. Opt., 48, 6716–6733, 2009.

- H2.13._Kuze, A., O'Brien, D. M., Taylor, T. E., Day, J. O., O'Dell, C., Kataoka, F., Yoshida,
 M., Mitomi, Y., Bruegge, C., Pollock, H., Basilio, R., Helmlinger, M., Matsunaga, T.,
 Kawakami, S., Shiomi, K., Urabe, T., and Suto, H.: Vicarious calibration of the GOSAT
 sensors using the Railroad Valley desert playa, IEEE Trans. Geosci. Remote Sens., 49,
 1781-1795, doi:10.1109/TGRS.2010.2089527, 2011.
- 6 <u>13.14.</u> Kuze, A., Suto, H., Shiomi, K., Urabe, T., Nakajima, M., Yoshida, J., Kawashima, T.,
 7 Yamamoto, Y., and Kataoka, F.: Level 1 algorithms for TANSO on GOSAT: Processing
 8 and on-orbit calibration, Atmos. Meas. Tech., 5, 2959–3018, 2012.
- 9 14.15. Kuze, A., Taylor, T.E., Kataoka, F., Bruegge, C. J., Crisp, D., Harada, M., Helmlinger, 10 M., Inoue, M., Kawakami, S., Kikuchi, N., Mitomi, Y., Murooka, J. Naito, M., O'Brien, D. 11 M., O'Dell, C. W., Ohyama, H., Pollock, H., Schwandner, F. M., Shiomi, K., Suto, H., Takeda, T., Tanaka, T., Urabe, T., Yokota, T., and Yoshida, Y.: Long term vicarious 12 13 calibration of GOSAT sensors; techniques for error reduction and new estimates of 14 degradation factors, IEEE Trans. Geosci. Remote Sens., 52, 3991-4004, 15 doi:10.1109/TGRS.2013.2278696, 2014.
- 16 <u>15.16.</u> Kuze, A., Shiomi, K., Suto, H., Kataoka, F., Crisp, D., Schwandner, F. M., Bruegge, C.,
 17 and Taylor, T.E.: GOSAT-OCO-2 synergetic CO₂ observations over calibration &
 18 validation sites and large emission sources, AGU fall meeting, San Francisco, 2015.
- 19 <u>16.17.</u> Leifer, I., Melton, C., Tratt, D. M., Kuze, A., Buckland, K. N., Butz, A., Deguchi, A.,
 20 Eastwood, M. L., Fischer, M. L., Frash, J., Fladeland, M. M., Gore, W., Iraci, L. T., Johnson,
 21 P. D., Kataoka, F., Kolyer, R., Leen, J. B., Quattrochi, D. A., Shiomi, K., Suto, H., Tanaka,
- T., Thompson, D. R., Yates, E. L., Damme, M. V., and Yokota, T.: The relationship
 between fossil and dairy greenhouse gas emissions and complex urban land-use patterns
 by in situ and remote sensing data from surface mobile, airborne, and satellite instruments,
- AGU fall meeting, San Francisco, 2015.
- 17.18. Long, D. A., and Hodges, J. T.: On spectroscopic models of the O₂ A band and their
 impact upon atmospheric retrievals, J. Geophys. Res. 117, D12309,
 doi:10.1029/2012JD017807, 2012.
- 18.19. O'Brien, D. M., Polonsky, I., O'Dell, C., Kuze, A., Kikuchi, N., Yoshida, Y., and Natraj,
 V.: Testing the polarization model for TANSO-FTS on GOSAT against clear-sky
 observations of sun-glint over the ocean, IEEE Trans. Geosci. Remote Sensing, 5199-5209,
 doi:10.1109/TGRS.2012.2232673, 2013.

19.20. O'Dell, C., Polonsky, I. N., Frankenberg, C. Crisp, D. Eldering, A. Gunson, M. R., 1 2 Wunch, D., Wennberg, P. O., and Chevallier, F.: Analysis of four years of GOSAT data 3 through the ACOS B3.4 retrieval algorithm, AGU fall meeting, San Francisco, 2013. 4 20.21. Sanghavi, S., Lebsock, M., and Stephens, G.: Sensitivity analysis of polarimetric O2 5 A-band spectra for potential cloud retrievals using OCO-2/GOSAT measurements, Atmos. 6 Meas. Tech., 8, 3601–3616, 2015. 7 21-22. Shiomi, K., Kawakami, S., Kuze, A., Suto, H., Hashiguchi, T., Kataoka, F., Higuchi, R., 8 Bruegge, and C., Schwandner, F.: On-orbit lunar calibration compared with vicarious 9 calibration for GOSAT, AGU fall meeting, San Francisco, 2013. 10 22.23. Suto, H., Frankenberg, C., Crisp, D., and Kuze, A.: Characterization and correction of 11 non-linearity effect on oxygen spectra of TANSO-FTS onboard GOSAT, San Francisco, 12 AGU fall meeting, 2011. 13 23.24. Suto, H., Yoshida, J., Desbiens, R., Kawashima, T., and Kuze, A.: Characterization and 14 correction of spectral distortions induced by microvibrations onboard the GOSAT Fourier transform spectrometer, Appl. Opt., 52, 4969-4980, 2013a. 15 16 24.25. Suto, H., Kuze, A., Shiomi, K., and Nakajima, M.: Space-based carbon monitoring by 17 GOSAT and GOSAT-2: Lessons learned from GOSAT in-orbit operation and towards 18 better accuracy of XCO₂ observation, San Francisco, AGU fall meeting, 2013b. 19 25.26. Suto, H., Butz, A., and Kuze, A.: Correction of spectral distortion on Oxygen A-band 20 due to non-linear phase delay onboard TANSO-FTS/GOSAT, San Francisco, AGU fall 21 meeting, 2014. 26.27. Thompson, D. R., Benner, D. C., Brown, L. R., Crisp, D., Devi, V. M., Jiang, Y., Natraj, 22 23 V., Oyafuso, F., Sung, K., Wunch, D., Castano, R., and Miller, C. E.: Atmospheric 24 validation of high accuracy CO₂ absorption coefficients for the OCO-2 mission, J. Quant. Spectrosc. Radiat. Transfer, 113 (17), 2265-2276, 2012. 25 26 27.28. Turner, A. J., Jacob, D. J., Wecht, K. J., Maasakkers, J. D., Biraud, S. C., Boesch, H., 27 Bowman, K. W., Deutscher, N. M., Dubey, M. K., T. Griffith, D. W., Hase, F., Kuze, A., Notholt, J., Ohyama, H., Parker, R., Payne, V. H., R. Sussmann, Velazco, V. A., 28 Warneke, T., Wennberg, P. O., and Wunch, D.: Estimating global and North American 29 30 methane emissions with high spatial resolution using GOSAT satellite data, Atmos. Chem. 31 Phys., 15, 7049-7069, 2015.

1	28.29. Toon, G. C., Blavier, J. F., Sen, B., Kleinboehl, A., Boesch, H., Sung, K., Nair,
2	Frankenberg, and C., Aaron, S.: Improved solar reference spectrum, Pasadena,
3	International Workshop on Greenhouse Gas Measurements from Space, 2015.
4	29.30. Uprety, S., and Cao, C.: VIIRS bias analysis using Hyperion, Hyspiri Symposium, 2015.
5	30.31. Veefkind, J., Aben, I., McMullan, K., Förster, H., de Vries, J., Otter, G., Claas, J., Eskes,
6	H., de Haan, J., Kleipool, Q., van Weele, M., Hasekamp, O., Hoogeveen, R., Landgraf, J.,
7	Snel, R., Tol, P., Ingmann, P., Voors, R., Kruizinga, B., Vink, R., Visser, H., and Levelt,
8	P.: TROPOMI on the ESA Sentinel-5 precursor: a GMES mission for global observations
9	of the atmospheric composition for climate, air quality and ozone layer applications, the
10	Sentinel missions - new opportunities for science, Remote Sens. Environ., 120, 70-83,
11	doi:10.1016/j.rse.2011.09.027, 2012.
12	31.32. Wunch, D., Toon, G. C., Blavier, JF.L., Washenfelder, R. A., Notholt, J., Connor, B.
13	J., Griffith, D.W.T., Sherlock, V., and Wennberg. P. O.: The Total Carbon Column
14	Observing Network. Phil. Trans. R. Soc. A, 369, 2087–2112, 2011
15	32.33. Yoshida, Y., Kikuchi, N., Morino, I., Uchino, O., Oshchepkov, S., Bril, A., Saeki, T.,
16	Schutgens, N., Toon, G. C., Wunch, D., Roehl, C. M., Wennberg, P. O., Griffith, D. W. T.,
17	Deutscher, N. M., Warneke, T., Notholt, J., Robinson, J., Sherlock, V., Connor, B.,
18	Rettinger, M., Sussmann, R., Ahonen, P., Heikkinen, P., Kyrö, E., Mendonca, J., Strong,
19	K., Hase, F., Dohe, S., and Yokota, T.: Improvement of the retrieval algorithm for GOSAT
20	SWIR XCO2 and XCH4 and their validation using TCCON data, Atmos. Meas. Tech., 6,
21	1533-1547, doi:10.5194/amt-6-1533-2013, 2013.
22	

Pointing	Pointing offset	L1B V161 and earlier		L1B V201	
system	-	Geolocation	Correction	Geolocation	Best- estimate geolocation
Primary (PM-A)	Time dependent (correction table of every two week) (AT and CT angles independent)	Not corrected	Users have to use the correction table	Not corrected	Corrected
Secondary (PM-B)	Constant since Feb. 2015 CT angle dependent	Not corrected	provided from NIES GUIG	Corrected	Corrected (The same as the geolocation)

2 Table 1. Pointing offset and geolocation information in the L1B product.

	2009	2010	2011	2012	2013	2014	2015 -
Milestone	* Launch					* * Solar paddle accident Unstable Pointing	* * Switching Pointing mechanism Cryocooler suspend
FTS Nominal Pointing Pattern	5p-CT			3p-CT		1, 3 p-CT	Зр-СТ
FTS Pointing		Primary					Secondary
FTS interferogram			No bias			800 fring	ges bias
FTS Operation	SWIR (S) and TIR (T)						S& T

- 6 Note: There is no change in the operation of TANSO-CAI and CAM
- **Fig. 1.** Long-term operation status..





Fig. 2. Long-term ZPD position from the center of the interferogram with periodic correction
operations. The optical center of the interferogram is 38273 half laser fringes. The vertical
lines represent the time of 3 major system anomalies: solar paddle, pointing mechanism
change and cryocooler suspension and restart.



Fig. 3. Detected laser signal amplitude of dephase and fringe and the minimum level of 0.13V
(solid level) to control the FTS mechanism.



Fig. 4. Pointing mechanisms and optics layout of TANSO-FTS.



1

2

Fig. 5. Solar irradiance monthly calibration data from the back side of the onboard Spectralon diffuser, which indicates the change from the first measurement in space after correction for the distance between the satellite and the Sun and the angle of incidence of the solar beam upon the diffuser. The vertical lines represent the time of vicarious campaigns.



Fig. 6. RDF for six years from seven annual vicarious calibration campaigns of (a) TANSO-FTS and (b) TANSO-CAI. Each symbol represent calibration points calculated from individual surface measurement. The lines in (a) show the model derived from the onboard solar diffuser data.

5

6

7



Fig. 7. Long-term pointing offset for grid observations: AT optical angle (circle) and CT
(square). Since August 2010, the grid observation pattern has changed from the 5-point CT
mode to the 3-point CT scan mode. From 23, January 2015, the secondary pointing system is
used.



X-AXIS (Re-sampling)

- (1) FTS mechanism scan speed instability correction for medium gain (2 sinusoidal sources) (V110 and later)
- (2) Sampling interval non-uniformity correction (SINUC) (V150 issue, not applied in V161, modified in V201)
- (3) Analogue circuit intensity dependent phase delay correction (V201)
- (4) Doppler shift due to image motion compensation (forward to backward viewing) (not corrected)

Y-Axis (Intensity correction)

- (1) Intensity variation (low frequency) component correction (V050, modified in V201)
- (2) Detector nonlinearity correction (Band 4) (V110 and later)
- (3) Band 1 high gain amplifier nonlinearity correction (V150, modified in V201)
- (4) ADC nonlinearity (not corrected, V130 issue)
- 2 Fig. 8. Corrections in the Level 1 B processing in the interferogram domain. V050, V110,
- 3 V130, V150, V161, and V201 are versions of the Level 1B. The items with italic letters are
- 4 described in this paper.
- 5



2 Fig. 9. TANSO-FTS L1B V201 data processing flow. Hatched boxes and italic letters show

3 the modification from L1B V161. The procedures are also modified in L1B V201.





3 Fig. 10. Band 1 analogue circuit block diagram and correction in L1B V201.



5 Fig. 11. Intensity dependent phase of the Band 1 P (B1P) (solid line) and S (B1S) (dotted line)

6 high gain analogue circuit. Higher gain B1S has larger dependency.



- 2 Fig. 12. Weighting function for interferogram with bias larger than 100 half laser fringes.



Fig. 13. Estimated calibration uncertainty by adding systematic bias error in case of viewing nadir (06:19:10 UTC, on 23 December 2010) (solid line) and 280 K BB target (bold line).



Fig. 14. Clear sky data (a) with and (b) without introducing dithering observation over the
Amazon in September 2014. Upper and lower triangles are categorized as tropical rain forest
and Cerrado, respectively. The repeated observation location are overwritten.



4 Fig. 15. (a) Glint observation area extension by tracking along the principal plane of reflection

5 before (left) and after (right) 9 September 2014, and (b) clear sky data point distribution after

6 extension during 7–9 June 2015.